

**DATASHEET** SKU: 078511HH

## 3M PELTOR CH-3 Headset

# with Push-To-Talk, Headband

The 078511HH Headset is a provides hearing protection and is designed for use with communication equipment. It has an electret microphone with extremely effective level dependent function, so the wearer's voice can be heard clearly while other noises are filtered out. The hearing protectors also attenuate ambient noise, protecting the wearer's hearing while enabling him to hear communication.

The 078511HH comes with a H-termination, however the Headset can use interchangeable cords that make it easily adaptable to any use. You no longer need multiple headsets if you have several communication radios with different connectors.

The 078511HH is equipped with a PTT/respond button, which is used to broadcast on a communication radio or to receive calls through a mobile phone. The button has a logical location on the left ear cup and is easy to operate even with gloves.



#### **FEATURES**

- High-attenuating shells with optimised acoustic design
- Excellent space for ears for the best possible sound quality and comfort
- Effective noise compensation for clear and reliable communication
- Quick Positioning integrated microphone boom for easy handling
- Soft, wide foam and fluid-filled sealing rings and individually sprung headband wires of stainless sprung steel
- PTT button on the cup

#### **SPECIFICATIONS**

Frequency (Hz)	125	250	500	1000	2000	4000	8000
Mean Attenuation (dB)	17.7	27.1	33.8	38.1	36.2	33.6	37.1
Standard Deviation (dB)	2.9	2.1	2.4	2.6	2.3	2.5	2.2
Assumed Protection (dB)	14.8	25	31.4	35.5	33.9	31.5	34.9

## **WARRANTY**

1 year (Please refer to Benelec Terms and Conditions)

Website: benelec.au

